

- **GB122W1 easily converts a single socket into a double socket**
- **GB223W easily converts a double socket into a triple socket**
- **Quick and easy to fit**
- **Supplied with 2 x M3.5 screws to fit existing wall box**
- **Conforms to BS 1363**

IMPORTANT

This product should be installed by a competent person and in accordance with the current IET Wiring Regulations, and Building Regulations. If in doubt, consult a qualified electrician.

INSTALLATION

1. **TURN OFF** the electricity supply at the consumer unit or fuse box before beginning any fitting. Take out the appropriate fuse or turn off at the circuit breaker.
2. Remove the existing single or twin socket from the wall, typically by unscrewing the two retaining screws on either side of the socket faceplate. Disconnect the wiring conductors from the socket.
3. Fit the wiring conductors into the correct terminals of the socket converter:

LIVE (L) = RED OR BROWN

NEUTRAL (N) = BLACK OR BLUE

EARTH (E) = GREEN/YELLOW

Check that all bare wires are firmly housed in the correct terminals before clamping, tightening in place with the terminal screw. The screw must clamp the copper wire not the insulation fitted to the wire.

4. Using the two screws supplied, attach the socket converter to the original flush metal or dry lining box. Ensure that no wiring becomes trapped when tightening the screws.
5. Turn the mains electricity back on at the consumer unit or fuse box, replacing any fuse or reactivating the circuit breaker and test the installation is correctly wired.

PLEASE NOTE: Electricity is dangerous and can kill. If you are in any doubt how to fit your converter or there appears to be damage to the wiring, consult a qualified electrician.

The socket converter is intended for indoor use only. It is designed to fit a double metal knockout or dry lining box conforming to the relevant British Standard. A minimum of 2.5mm sq. 3 core cable should be used to wire mains sockets.

TECHNICAL INFORMATION

Rated Voltage: 13A / 230V

Class Type: I

IP Rating: IP20

Main Housing: White Urea

Terminal Holes: 3 x 2.5mm² Single
or Stranded cable

Supplied With: 2 x M3.5 screws

Dimensions:

GB122W1: H85 x W145 x D23mm

GB223W: H87 x W210 x D25mm
(D = front plate depth)

Conforms To: BS 1363-2:2016+A1:2018

GUARANTEE

Your GreenBrook socket converter is guaranteed for 1 year from the date of purchase. This is in addition to your statutory rights.

**PLEASE KEEP THESE INSTRUCTIONS
SAFE FOR FUTURE REFERENCE**

